

Keep your computers and peripherals running when the power goes out

Keep your computers and peripherals running when the power goes out



TRIGGER 1000

Features

- ✓ Green topology saves 50% energy on AC mode.
- ✓ Built-in super smart charger
- ✓ Changing capability at low input voltage.
- ✓ Microprocessor control guarantees high reliability.
- ✓ Boost and Buck AVR for voltage stabilization.
- ✓ Off-mode auto charging.
- ✓ Auto-restart on AC is recovery.
- ✓ Cold start function.
- ✓ Built-in USB communication port and phone line protection.

TRIGGER 1000 LINE INTERACTIVE UPS SPECIFICATIONS		
MODEL		TRIGGER 1000
INPUT	Voltage	220/230/240VAC
	Voltage Range (In-built-AVR)	162-290 VAC
OUTPUT	Voltage	220/230/240VAC
	Voltage Regulation (Batt. Mode)	±10%
	Frequency	60Hz or 50 Hz
	Frequency Regulation (Batt. Mode)	±1Hz
	Output Wave-form	Modified sine-wave
BATTERY	Battery Type & Number	12V / 9AH x 1 pc
	Backup Time (at 1PC load with 15" monitor)	25 - 30 minutes
	Recharge Time	08 hours to 90% after complete discharge
TRANSFER TIME	Typical	2-6 ms
PROTECTION	Full Protection	Over Discharge, Overcharge and Overload Protection
PHYSICAL	Dimension (DxWxH) mm	330 x 100 x 140
	Net Weight (kgs)	6.5kg
INTERFACE	USB	Windows 98SE/ME/NT 4.X/ 2000/2003/XP/Vista/2008
OUTPUT CONNECTORS	Backup Only	3 x IEC Telephone Line Protector